









Selector Guide





General Purpose Relays





Series	R02	R06	R10	R12
				
Features	<ul style="list-style-type: none"> Dust Cover Octal-Type Plug 	<ul style="list-style-type: none"> Open Frame Solder Terminals Multi-Pole Switching 	<ul style="list-style-type: none"> Dust Cover .187" Quick Connect Terminals 	<ul style="list-style-type: none"> Dust Cover Slightly Larger than One Cubic Inch
Contact Arrangement	SPDT, DPDT, 3PDT	SPDT, DPDT, 3PDT	SPDT, DPDT, 3PDT	DPDT, 4PDT
Contact Ratings	10A @ 28VDC/120VAC	10A @ 28VDC 12A @ 120VAC	10A, 11A, 12A @ 28VDC/120VAC	1A, 3A, 5A @ 28VDC/120VAC
Coil Voltage	6, 12, 24, 120, 240VAC 6, 12, 24, 110VDC	24, 120VAC 6, 12, 24, 48, 110VDC	12, 24, 120, 240VAC 12, 24, 110VDC	12, 24, 120, 240VAC 6, 12, 24, 48, 110VDC
Nominal Coil Power AC Types DC Types	2.0, 2.75, 3.0, 3.9VA 1.0, 1.2, 1.5W	2.0, 2.75VA 1.0W	2.0, 2.75VA 1.2W	1.2VA 0.9mW
Options () Suffix	Indicator Lamp (N) Push-to-Test Button (B) Hermetically Sealed (H) Mechanical Indicator (M)		Indicator Lamp (N) Push-to-Test Button (B) Flange Mount (F)	PC Board Mount (P) Indicator Lamp (N) Hermetically Sealed (H) Push-to-Test Button (B) Bifurcated Contact (T)
Page	17-18	21	22-23	24-25

General Purpose Relays (Cont'd)

Series	R14	R16	R17	R47
				
Features	<ul style="list-style-type: none"> Dust Cover .187" Quick Connect Terminals 	<ul style="list-style-type: none"> Dust Cover 	<ul style="list-style-type: none"> Plug-In Terminals Encapsulated Coil for Protection Clear See-Thru Cover 	<ul style="list-style-type: none"> .187" Quick Connect Terminals Upper Mounting Bracket Type for Easy Wiring and Mounting
Contact Arrangement	SPDT, DPDT, 3PDT, 4PDT	DPDT, 4PDT, 6PDT	DPDT, DPDT-NO, 4PDT	SPST-NO, SPDT
Contact Ratings	10A, 15A @ 28VDC/120VAC	3A, 5A @ 28VDC/120VAC	10A @ 28VDC/300VAC	15A @ 24VDC/220VAC
Coil Voltage	12, 24, 120, 240VAC 6, 12, 24, 110VDC	120VAC 5/6, 12, 24VDC	24, 120VAC 24, 115/125VDC	24, 120VAC
Nominal Coil Power AC Types DC Types	1.2VA 0.9mW	1.5, 2.5VA 0.5, 0.75, 1.0W	5VA 1.8, 2.5W	1.3VA -
Options () Suffix	PC Board Mount (P) Flange Mount (F) Indicator Lamp (N)	PC Mount (P) Bifurcated Contact (T)		
Page	26-27	28-29	30	50

Selector Guide

Gen Purp Relays (Cont'd)		Power Relays		
Series	R55	R04	R18	R45
				
Features	<ul style="list-style-type: none"> • .250" Quick Connect Terminals • Flange Mount • Clear See-Thru Cover 	<ul style="list-style-type: none"> • Open Frame • Screw Terminals • Heavy Duty 	<ul style="list-style-type: none"> • Dust Cover • Jones Plug Terminals • Switches Tungsten Lamp Loads 	<ul style="list-style-type: none"> • Epoxy Sealed • Single-Pole Switching • .250" Quick Connect Terminals • Printed Circuit Terminals on Bottom
Contact Arrangement	SPDT, DPDT	SPST-NO, SPDT, DPST-NO, DPDT	DPDT	SPST-NO, SPDT
Contact Ratings	20A, 25A @ 28VDC/300VAC	30A @ 28VDC/120VAC	20A @ 28VDC/120VAC	20A, 30A @ 28VDC/300VAC
Coil Voltage	24, 120, 240VAC 12, 24VDC	12, 24, 120, 240VAC 12, 24, 110VDC	120VAC	5, 12, 24VDC
Nominal Coil Power AC Types DC Types	2.75, 3.0VA 1.2W	10VA 2.0W	4.0VA -	- 600mW, 900mW
Options () Suffix				Flange Mount (F)
Page	58	19-20	31	48

Power Relays (Cont'd)			Buzzers	
Series	R54	RLY16 & 17	RLY74 & 75	RB
				
Features	<ul style="list-style-type: none"> • Open Frame • .125" Quick Connect Terminals • Heavy Duty • 10A Tungsten Rating 	<ul style="list-style-type: none"> • Open Frame • Heavy Duty • Screw Terminals • Buzz-Free Shaded AC Coil 	<ul style="list-style-type: none"> • Heavy Duty • Multicontact • .250" Quick Connect Terminals 	<ul style="list-style-type: none"> • AC Operated • Lightweight • Audible Signal Source
Contact Arrangement	SPST-NO DM	4PDT	SPDT, DPDT	
Contact Ratings	30A @ 28VDC/120VDC	25A @ 277VAC 10A @ 28VDC	20A @ 277VAC	
Coil Voltage	24, 120, 240VAC 12, 24, 110VDC	24, 120, 240VAC 12, 24VDC	24, 120, 240VAC 12, 24VDC	12, 24, 120, 240VAC
Nominal Coil Power AC Types DC Types	3VA 1.5W	14VA 4.4W	4VA 3-4.5W	3VA -
Options () Suffix				
Page	57	79	82	111